

Security

A section for viewing information about the device password, Read-only FTP user status, and changes

Figure 1 - Chapter security

The screenshot shows a software interface for managing security settings. At the top, there's a message 'Settings saved: 5 days ago' and three buttons: 'Save settings', 'Default', and 'Help'. Below this, there are two main sections: 'DVR password' and 'Read-only FTP user'. The 'DVR password' section contains a field with four asterisks ('****') and a small info icon. The 'Read-only FTP user' section contains two fields: 'Username' with the value 'user' and 'Password' with four asterisks ('****').

Table 1 - Security parameters description

Parameter	Parameter description
DVR password	The device password is displayed when hovering over the field
Read-only FTP user	The name of Read-only FTP user
Password	Password of Read-only FTP user

To set the default settings, click the **Default** button. To save settings in NVR click **Save settings** button.

From:
<https://docs.bitrek.video/> - Bitrek Video Wiki

Permanent link:
<https://docs.bitrek.video/doku.php?id=en:security>

Last update: **2024/04/18 12:26**